


SPECIFICATION SHEET

MR11 COB LED | 3W 6-30VDC



APPLICATION

Emergency Lighting Remote Heads

FEATURES

- Save 85% energy cost(replace 20 Watt Halogen bulbs)
- Low Surge, specially designed for the emergency lighting customers
- Wide DC input: 6-30VDC
- High efficacy Lumen output, >99LM/W
- GU5.3 base
- 38 degree beam angle
- 5 year limited warranty (see valeralighting.com for details)



CERTIFICATIONS

- RoHS
- FCC

PERFORMANCE

Item #	Voltage
311505301	6-30VDC
Shape	CCT
MR11	5000K
Lumens	CRI
299	80
Wattage	Base
3W	GU5.3
LPW	Life/Hours
99	50,000
Technology	Dimmable
COB	No

ORDERING GUIDE

Series
3W MR11
Voltage
6-30VDC
Beam Angle
38, 60
CCT
3000, 4000, 5000, 6000, 7000
Base
GU5.3, GU10

PRE-BUILT INVENTORY

Ordering Code
311505301
Description
3W 6-30VDC
Specification
MR11 3W 6-30VDC INPUT CCT 5000K 38DEGREE, GU5.3