


# SPECIFICATION SHEET

## MR16 COB LED | 4W 5-27VDC



### APPLICATION

Emergency Lighting Remote Heads

### FEATURES

- Save 85% energy cost( replace 25 Watt Halogen bulbs)
- Low Surge, specially designed for the emergency lighting customers
- Wide DC input: 5-27VDC
- High efficacy Lumen output, >100LM/W
- GU5.3 base
- 38 degree beam angle
- 5 year limited warranty (see valeralighting.com for details)



### CERTIFICATIONS

- RoHS
- FCC

### PERFORMANCE

<b>Item #</b>	<b>Voltage</b>
416505301	5-27VDC
<b>Shape</b>	<b>CCT</b>
MR16	5000K
<b>Lumens</b>	<b>CRI</b>
419	80
<b>Wattage</b>	<b>Base</b>
4W	GU5.3
<b>LPW</b>	<b>Life/Hours</b>
104	50,000
<b>Technology</b>	<b>Dimmable</b>
COB	No

### ORDERING GUIDE

<b>Series</b>
4W MR16
<b>Voltage</b>
5-27VDC
<b>Beam Angle</b>
38, 60
<b>CCT</b>
3000, 4000, 5000, 6000, 7000
<b>Base</b>
GU5.3, GU10

### PRE-BUILT INVENTORY

<b>Ordering Code</b>
416505301
<b>Description</b>
4W 5-27VDC
<b>Specification</b>
MR16 4W 5-27VDC INPUT CCT 5000K 38DEGREE, GU5.3